

Primed Voltage Stabilizer

GTR95 M/S
(CV.286)

Limit Ratings

| | |
|--------------------------------------------------------------------|-------|
| Minimum anode current | 2 mA |
| Maximum anode current | 10 mA |
| Minimum anode supply voltage when primer is connected as (1) below | 110 V |
| (2) below | 125 V |

Primer Connections

1. To +150 V via 270 k Ω , or any other arrangement causing the primer current to be between 150 and 500 μ A.
2. Through 3.3 k Ω to the main anode.

Characteristics

| | |
|--------------------------------------------------------------|----------------------------|
| Running voltage at 5 mA | 90—100 V |
| Maximum change in V_R for a current change from 2 to 10 mA | 5 V |
| Impedance | 350 Ω |
| Primer striking volts | 125 V |
| Primer V_R before anode take-over | 108 V |
| Maximum noise within the working range | 15 mV r.m.s. |
| Noise at 2 mA | Approx. 350 μ V r.m.s. |

GTR95M/S

(CV.286)


Primed Voltage Stabilizer

Mechanical Data

Mounting position
Weight
Base

Any
7.1 g (nominal)
B7G

Base Connections
(underside view)



Pin 1 }
2 } Cathode
3 }
4 } Primer
5 }
6 } Anode
7 }

