

FERRANTI

VACUUM HIGH VOLTAGE RECTIFIER

A miniature indirectly heated Half-Wave High Voltage Rectifier.

PHYSICAL DETAILS.

Base	B7G.
Top Cap	Skirted Miniature.
Max. Overall Length	60 mm. ($2\frac{3}{8}$ in.).
Max. Seated Height	53 mm. ($2\frac{1}{4}$ in.).
Max. Diameter	19 mm. ($\frac{3}{4}$ in.).
Mounting Position	Any.

BASE CONNECTIONS.

Pin 1—Cathode.	Pin 5—Cathode.
Pin 2—Cathode.	Pin 6—Cathode.
Pin 3—Heater.	Pin 7—Cathode.
Pin 4—Heater.	Top Cap—Anode.

HEATER.

Heater Voltage	4.0 volts.
Heater Current	0.5 amp.


RATINGS*

Max. P.I.V. (no load)	14.0 kV.
Max. P.I.V. (working)	11.5 kV.
Max. R.M.S. Input Voltage	5.0 kV.
Max. Peak Anode Current	80 mA.
Max. Rectified Current	15 mA.
Max. Reservoir Condenser	1.0 μ F.
Min. Supply Impedance	30,000 ohms.
†Min. Delay for H.T. switching	30 secs.
Max. Operating Frequency	100 kc/s.


*The above Ratings are "Absolute" and apply to operation at 50 c/s. with a capacitor input filter and delayed switching.

†This valve may be used with simultaneous switching providing the R.M.S. input voltage is not more than 3.5 kV. and the rectified current does not exceed 3.0 mA.

HR3



Base
Connections
Underside View
of Base



All Dimensions
shown are in
millimetres
(max.).





HR3

