

T.	Image 1	Image 2	U_f	I_f	U_{tr}	I_o	R_{tr}	C_F
			V	A	V	mA	Ω	μF
AX 50	eur	1	4	3,75	500	275	200	64
AZ 50	eur	2	4	3	$\left\{ \begin{array}{l} 500 \\ 300 \end{array} \right.$	$\left\{ \begin{array}{l} 250 \\ 300 \end{array} \right.$	$\left\{ \begin{array}{l} 200 \\ 100 \end{array} \right.$	$\left\{ \begin{array}{l} 64 \\ 16 \end{array} \right.$
BO-188	CCCP	2	4	2		500	155	200
BO-197	CCCP	2	4	5	250	300	100	16
PV 200/600	Tu	2	4	3,4	$\left\{ \begin{array}{l} 600 \\ 500 \end{array} \right.$	$\left\{ \begin{array}{l} 200 \\ 260 \end{array} \right.$	$\left\{ \begin{array}{l} 100 \\ 100 \end{array} \right.$	$\left\{ \begin{array}{l} 40 \\ 40 \end{array} \right.$
RGN 2504	TIf	2	4	2,3		500	180	
RGN 4004	TIf	2	4	4	350	300		
U 18	MOG	2	4	3,5	$\left\{ \begin{array}{l} 850 \\ 500 \end{array} \right.$	$\left\{ \begin{array}{l} 125 \\ 250 \end{array} \right.$	$\left\{ \begin{array}{l} 180 \\ 180 \end{array} \right.$	$\left\{ \begin{array}{l} 8 \\ 16 \end{array} \right.$
U 18/20	MOG	2	4	2,4		500	250	180
UU 8	Maz	3	4	2,8	350	250	100	16
Z 2 c ¹⁾	eur	4	4	4	400	300 ($U_{fjk} = 80 V$)		

1) vide *4

Equivalents

APV 4	Tu = RGN 2504	RO 452	Rtn = RGN 2504
AZ 150	TIf = AZ 50	RV 200/600	Tu = BO-197
E 4 F	Mul = RGN 2504	TV 100	Dar = RGN 2504
E 4 G	Mul = RGN 4004	TV 120	Dar = RGN 4004
FW 4-500	Mul = AZ 50	UU 10	Maz = RGN 2504
FW 4-800	Mul = U 18	V 100	Dar = RGN 2504
G 2 c ¹⁾	Sim = Z 2 c	VG 421	Sat = RGN 2504
G 2504	Val = RGN 2504	VG 3630	Hog = RGN 4004
G 4004	Val = RGN 4004	W 10	Fot = RGN 2504
G 4180	Tri = RGN 2504	4 BX 1	CCCP = BO-188
G 4250	Val = RGN 2504	4 GG 2	TKD = RGN 2504
G 4300	Tri = RGN 4004	4 GG 3	TKD = RGN 4004
G 4400	Val = RGN 4004	4/100 BU	Cos = AZ 50
G 4460	Val = RGN 4004	45 IU	Cos = U 18
GR 4	Fer = RGN 4004	240 NG	Low = RGN 2504
KL 76303	Kgf = RGN 2504	1815	Phl = RGN 2504
KL 77305	Kgf = RGN 4004	1817	Phl = RGN 4004
PV 4201	Tu = RGN 2504	4100 BU	Cos = AZ 50
RG 24	Rec = RGN 4004	76303	Kgf = RGN 2504
RO 433	Rtn = RGN 4004	77305	Kgf = RGN 4004



